

dimax


PARLANTE ALTAVOZ 15 + 2 MICRÓFONOS VHF

L006



> CARACTERÍSTICAS

- Caja de altavoz a batería de 15"
- Imán del woofer: 15" 40oz, 50 mm VC
- Tweeter: controlador VC de 25 mm
- Potencia de salida: 180 vatios RMS (con Toshiba C5198/1941 original)
- Funciones: USB/SD/FM/BT con TWS/Indicación de voz/Prioridad de micrófono/REC/ECHO/Ecualizador quintuple/Pantalla LCD/Salida de altavoz/LUZ LED
- Accesorios: 2 micrófonos inalámbricos (VHF), 1 control remoto, 1 cable de alimentación de 1,8 m, 1 soporte para altavoz
- Batería: 12 V 7 AH
- Impedancia: 8 ohmios
- Fuente de alimentación: 220 V CA, 12 V CC



1. Bluetooth light
- Red: Bluetooth name search
- Blue: Bluetooth match
2. Remote Window
3. Control button of USB, MMC, FM, BT, RECORD
- REC: RECORD by inserting a USB/MMC through the line into the speaker
4. LCD Display
5. MMC Card
6. USB Port
7. MIC input with XLR and 6.35mm connectors
8. MIC level
9. Stereo input and output with RCA
10. Button to switch between line and MP3
11. Graphic equalizer
12. Echo effect
13. Master knob to adjust the volume of speaker
14. Line MP3 level
15. Aux in
16. MIC Priority
17. Volume control of wireless microphone
18. Antennas of wireless microphone
19. On/Off button
- When it is on status, the wireless microphone could work; when it is off, the microphone couldn't work.
20. Battery indicator
21. External charge
22. Battery FUSE
23. Power Socket
24. Power Switch
25. Speaker Output
26. Led power

